You can search for the updated part code through ITSELF web site.
URL : http://itself.sec.samsung.co.kr

7. Electrical Parts List

7-1 CF21K22TSXXEF

Level	Loc. No.	Code No.	Description ; Specification	Remark
			ASSY PCB MISC-A/V FRONT	
1		AA94-12517A	ASSY PCB MISC-A/V FRONT;(..73,..H1),KS1A	
2	CN702	AA39-20112E	LEAD CONNECTOR-ASSY;,9P,300,YBNH025-09,6	
2		0202-000008	SOLDER-WIRE;S63S-W3.0,S63S,D3,63Sn/37Pb,	
2		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	
2		0204-001024	FLUX;DF-98TVS,-,20%,-	
2		0204-000442	SOLVENT;1M-1000,C3H70H,96,-	
2	JE601	3722-000143	JACK-PHONE;1P(VER),3.4PI,AG,BLK,NO	
2	JA702	3722-000506	JACK-PIN;2P,3.6mm,-,AG	
2		AA97-13679A	ASSY AUTO-A/V FRONT;(..73,..H1),KS1A	
3	RE04	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
3	RE01	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
3	RE02	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
3	CE07	2202-000222	C-CERAMIC,MLC-AXIAL;3.3nF,20%,16V,Y5P,TP	
3	CE06	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
3	CE01	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
3	JE01	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
3	JE02	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
3	JE04	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
3	RE05	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
3	JE03	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
3	PCB	AA41-10903B	PCB-A/V FRONT;S15A,1L,FR-1,245x245x1.6T,	
3		0203-001123	TAPE-PAPER;#53131,T0.15,W6.0,L200000,YEL	
3	LE01	2701-000158	INDUCTOR-AXIAL;22uH,10%,2.5x3.4mm	
			ASSY PCB MAIN	
1		AA94-12799A	ASSY PCB MAIN;CF21K2T,PHILIPS,KS1A	
2		AA97-13864A	ASSY AUTO;CF21K2,PHILIPS,KS1A	
3		HA68-02176A	LABEL;LABEL	
3	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 3	D811	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
3	D102	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 3	D801S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 3	D802S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 3	D803S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 3	D804S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
3	D501	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
⚠ 3	D803	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
3	D301	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
3	D304	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
⚠ 3	D401	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
3	D502	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
3	D503	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
3	D504	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
3	D812	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
3	D302	0402-001352	DIODE-RECTIFIER;GUF15G-20A,400V,1.5A,DO-	
3	DZ402	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
3	DZ807	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
3	DZ810	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
3	DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
3	DZ904	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
3	DZ905	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
3	DZ901	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
3	DZ101	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
3	DZ303	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
3	DZ803	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
3	DZ201	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
3	DZ204	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
3	DZ205	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
3	DZ207	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
3	DZ501	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
3	DZ502	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
3	DZ503	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
3	DZ504	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
3	DZ704	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
3	DZ808	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
3	DZ306	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
3	DZ307	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
3	DZ701	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
3	DZ702	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
3	DZ703	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
3	DZ801	0403-001140	DIODE-ZENER;RD10ESAB-T4,10V,9.19-10.30V,	
3	DZ302	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
3	DZ806	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
3	DZ802	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500mW,DO	
3	DZ203	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
3	DZ805	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
3	DZ301	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
3	DZ305	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
3	Q201	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
3	Q901	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
3	Q402	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
3	Q202	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
3	Q205	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
3	Q701	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
3	Q903	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
3	Q905	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
3	Q704	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
⚠ 3	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
3	R207	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
3	R905	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
3	R906	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
3	R218	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R602	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R205	2001-000011	R-CARBON;75KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R301	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
3	J125	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
3	R843	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
3	R618	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
3	R409	2001-000022	R-CARBON(S);33OHM,5%,1/2W,AA,TP,2.4X6.4M	
3	R823	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
3	R902	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R904	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R211	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R215	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R223	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R501	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R502	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R506	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R510	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R511	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R512	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R909	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R911	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R912	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R913	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R914	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	J137	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R213	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R718	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R933	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R934	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
3	R224	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R828	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R910	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R920	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R922	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R921	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R919	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R709	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R230	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R225	2001-001035	R-CARBON;91OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R918	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R926	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R210	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R723	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R721	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R916	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R917	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R220	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R901	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R903	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R907	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R908	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R214	2001-000490	R-CARBON;200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R206	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R829	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R929	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R208	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R108	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R202	2001-000689	R-CARBON;390KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R925	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R841	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R601	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R227	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R228	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R109	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R724	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R725	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R726	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R727	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R209	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R927	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R203	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R204	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R713	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R715	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R110	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R915	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R722	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R222	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R702	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R719	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R720	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R408	2001-001037	R-CARBON(S);0.39OHM,5%,1/2W,AA,TP,2.4X6.	
3	R504	2001-001062	R-CARBON(S);10MOHM,5%,1/2W,AA,TP,2.4X6.4	
3	R414	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
3	R806	2001-001108	R-CARBON(S);22KOHM,5%,1/2W,AA,TP,2.4X6.4	
3	R411	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
3	R405	2001-001116	R-CARBON(S);27OHM,5%,1/2W,AA,TP,2.4X6.4M	
3	R809	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
3	R810	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
3	R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
3	R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
3	R503	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
⚠ 3	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 3	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
3	R827	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
3	R315	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
3	R316	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
3	R403	2003-000784	R-METAL OXIDE(S);7.5Kohm,5%,2W,AF,TP,4x1	
3	R834	2003-001040	R-METAL OXIDE(S);47Kohm,5%,2W,AF,TP,3.9x	
3	R801	2003-002171	R-METAL OXIDE(S);150ohm,5%,2W,AG,TP,3.9x	
3	R402	2003-002178	R-METAL OXIDE(S);1Kohm,5%,2W,AG,TP,3.9x1	
3	R407	2003-002209	R-METAL OXIDE(S);47Kohm,5%,2W,AG,TP,3.9X	
3	R219	2004-001914	R-METAL;39Kohm,2%,1/8W,AA,TP,1.8x3.5mm	
3	R304	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
3	R305	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
3	R825	2008-000266	R-FUSIBLE(S);1ohm,5%,2W,AF,TP,3.9x10mm	
3	R824	2008-000294	R-FUSIBLE(S);33ohm,5%,2W,AF,TP,3.9x10mm	
3	R420	2008-001110	R-FUSIBLE(S);68ohm,5%,2W,AG,TP,3.9X12mm	
3	R814	2008-001112	R-FUSIBLE(S);2.4ohm,5%,2W,AG,TP,3.9x12mm	
3	R815	2008-001112	R-FUSIBLE(S);2.4ohm,5%,2W,AG,TP,3.9x12mm	
3	C904	2201-000180	C-CERAMIC,DISC;10NF,10%,50V,Y5V,TP,7X3MM	
3	C501	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
3	C302	2201-000259	C-CERAMIC,DISC;0.18NF,10%,500V,Y5P,TP,5.	
3	C303	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
3	C305	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
3	C908	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
3	C909	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
3	C408	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
⚠ 3	CR404S	2201-000639	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
3	C811	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
3	C814	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
3	C503	2201-000723	C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,16X5	
3	C703	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
3	C704	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
3	C106	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
3	C111	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
3	C105	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
3	C223	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
3	C224	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
3	C906	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
3	C505	2202-000825	C-CERAMIC,MLC-AXIAL;680pF,10%,50V,Y5P,TP	
3	C226	2202-000829	C-CERAMIC,MLC-AXIAL;0.82NF,10%,50V,Y5P,T	
3	C707	2301-000204	C-FILM,PEF;2.7nF,5%,50V,TP,7.4x3.9x13mm,	
3	C502	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
3	C109	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
3	C804	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
3	C805	2301-000235	C-FILM,PEF;3.9nF,5%,50V,TP,6.5x3.0x5.5mm	
3	C309	2301-000254	C-FILM,PEF;39nF,5%,50V,TP,7.5x3.5x6.5mm,	
3	C606	2301-000111	C-FILM,PEF;1.8nF,5%,50V,TP,6.5x3.0x5.5mm	
3	C217	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
3	C234	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
3	C407	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
3	C227	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
3	C248	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
3	C420	2305-000178	C-FILM,MPEF;10nF,5%,100V,TP,-,5mm	
3	C301	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
3	C215	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
3	C216	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
3	C233	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
3	C611	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
3	C613	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
⚠ 3	CR405S	2305-000382	C-FILM,MPEF;4.7nF,5%,400V,TP,-,5mm	
3	C103	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
3	C208	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
3	C210	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
3	C230	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
3	C803	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
3	C819	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
3	C913	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
3	C218	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
3	C204	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
3	C205	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
3	C231	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
3	C618	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
3	C225	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
3	C812	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
3	C817	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
3	C823	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
3	C915	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
3	C307	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
3	C308	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
3	C506	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
3	C820	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
3	C612	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
3	C604	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
3	C219	2401-000603	C-AL;1UF,20%,50V,GP,TP,5X11,2	
3	C212	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
3	C221	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
3	C605	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
3	C222	2401-000758	C-AL;0.22UF,20%,50V,GP,TP,5X11,5	
3	C827	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	

Level	Loc. No.	Code No.	Description ; Specification	Remark
3	C101	2401-001101	C-AL;330uF,20%,16V,GP,TP,8x11.5,5	
3	C802	2401-001192	C-AL;33uF,20%,50V,GP,TP,6.3x11,5	
3	C504	2401-001232	C-AL;4.7uF,20%,250V,GP,TP,10x12.5,5	
3	C209	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
3	C213	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
3	C229	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
3	C903	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
3	C910	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
3	C110	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
3	C214	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
3	C705	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
3	C706	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
3	C710	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
3	C711	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
3	C601	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
3	C206	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
3	C220	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
3	C709	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
3	C304	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
3	C306	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
3	C813	2401-002290	C-AL;47uF,20%,160V,GP,TP,13x20,5	
3	C406	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
3	L103	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
3	L202	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
3	L301	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
3	L302	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
3	L404	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
3	L903	2701-000158	INDUCTOR-AXIAL;22uH,10%,2.5x3.4mm	
3	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
3	L201	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
3	L205	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
3	L405	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
3	L902	2701-000180	INDUCTOR-AXIAL;33uH,5%,2.5x3.4mm	
3	L904	2701-000180	INDUCTOR-AXIAL;33uH,5%,2.5x3.4mm	
3	L702	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
3	L703	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
3	L704	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
3	L706	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
3	X901	2801-003937	CRYSTAL-UNIT;12MHz,25ppm,28-AAM,30pF,30o	
3	L403	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
3	L806	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
3	L808	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
3	Z202	2903-001040	FILTER-CERAMIC;TR,5.5/6.0/6.5MHz,-,1dB,-	
3	L802	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
3	L803	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
3	J910	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
3	SW901	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
3	SW902	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
3	SW903	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
3	SW904	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
3	SW905	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
3	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
3	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
3	EY101	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY401	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY402	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY403	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY404	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY405	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY406	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY407	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY408	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY409	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY410	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY411	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY412	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY414	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY415	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY416	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY417	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY419	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY420	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY421	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY422	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY423	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY501	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY801	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY802	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY803	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY807	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY808	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY809	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY810	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY813	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY818	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY819	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY821	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY822	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY823	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY824	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY825	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY827	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY828	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY829	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY830	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY833	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY850	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY851	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY852	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY853	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY860	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EY861	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
3	EL301	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
3	EL302	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
3	EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
3	EL404	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
3	EL407	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
3	EL408	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
3	EL501	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
3	EL502	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
3	EL601	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
3	EL602	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
3	EL603	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
3	EL604	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
3	EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
3	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
3	EL804	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
3	GT101	AA60-40014A	PIN-GT,ASSY;AUTO	
3	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	
3	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	
3	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	
3	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	
3	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	
3	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	
3	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	
3	GT807	AA60-40014A	PIN-GT,ASSY;AUTO	
3	R424	2004-001402	R-METAL(S);6.8Kohm,1%,1/2W,AA,TP,2.4x6.4	
3	R423	2004-001373	R-METAL(S);100Kohm,1%,1/2W,AA,TP,2.4x6.4	
⚠ 3	FD801S	3601-001163	FUSE-AXIAL LEAD;125V,7A,-,EPOXY,2.4X7.1M	
3	D807	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
3	D303	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
3	D809	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
3	C115	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
3	C211	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
3	C911	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
3	C822	2401-000711	C-AL;2200uF,20%,25V,GP,TP,16x25,7.5	
3	C806	2301-001435	C-FILM,PPF;1.5nF,5%,1.2kV,TP,15x8x12.5mm	
3	C207	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
3	C901	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
3	HIC01	AA13-20004W	IC HYBRID;-,PAP103T,SIP,6P,PRE-AMP,TP	
3	RW701	2011-001133	R-NETWORK;33K/24K/75x3,5%,1/8W,X,SIP,6P,	
3	PCB	AA41-00131H	PCB-MAIN;CS21D8,FR-1,1L,H,1.6T,245X245,K	
3	C702	2202-000210	C-CERAMIC,MLC-AXIAL;270pF,10%,50V,Y5P,TP	
⚠ 3	FP801S	3601-000281	FUSE-CARTRIDGE;250V,4A,TIME-LAG,GLASS,5.	
3	L101	2701-000171	INDUCTOR-AXIAL;330nH,10%,2.5x3.4mm	
3	Z203	2903-000181	FILTER-CERAMIC;BR,5.5MHz,-,-,-,TP,TPS5.5	
3	J101	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	L807	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
3	L804	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
3	C403	2401-000560	C-AL;1uF,20%,160V,GP,TP,6.3x11,5	
3	C615	2202-000253	C-CERAMIC,MLC-AXIAL;4.7nF,20%,16V,Y5R,TP	
⚠ 3	D804	0401-000006	DIODE-SWITCHING;BAV21,250V,250mA,DO-35,T	
⚠ 3	D805	0402-001470	DIODE-RECTIFIER;RU2BV1,800V,1A,DO-204AC,	
3	R808	2001-001138	R-CARBON(S);390OHM,5%,1/2W,AA,TP,2.4X6.4	

Level	Loc. No.	Code No.	Description ; Specification	Remark
3	R831	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
3	L104	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
3	L204	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
3	C203	2401-002462	C-AL;33uF,20%,16V,GP,TP,5x11,5	
3	R811	2003-002239	R-METAL OXIDE(S);100KOHM,5%,2W,AF,TP,3.9	
3	R812	2003-002239	R-METAL OXIDE(S);100KOHM,5%,2W,AF,TP,3.9	
3	R421	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
3	R413	2003-000532	R-METAL OXIDE(S);18ohm,5%,2W,AF,TP,4x12m	
3	R107	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	R840	2001-001122	R-CARBON(S);3.9KOHM,5%,1/2W,AA,TP,2.4X6.	
3	C818	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
3	C821	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
3	R728	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	R923	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	C603	2301-000247	C-FILM,PEF;33nF,5%,50V,TP,8.1x4.5x13mm,5	
3		0203-001123	TAPE-PAPER;#53131,T0.15,W6.0,L200000,YEL	
3	C102	2202-000279	C-CERAMIC,MLC-AXIAL;47pF,5%,50V,SL,TP,3.	
3	DZ401	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
3	DZ906	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
3	DZ907	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
3	DZ908	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
3	C107	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	C507	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	C508	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	D202	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J102	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J103	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J104	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J106	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J107	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J108	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J110	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J111	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J113	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J114	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J117	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J120	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J121	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J122	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J124	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J126	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J127	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J128	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J129	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J131	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J132	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J133	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J134	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J135	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J136	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J138	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J139	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J140	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J142	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J143	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J145	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J146	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J147	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J148	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J150	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J151	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J152	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J154	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J155	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J156	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J157	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J158	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J159	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J160	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J163	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J167	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J168	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J170	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J171	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J173	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J174	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J175	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J176	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J182	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J185	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J186	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J187	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J189	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J190	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J192	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J193	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J195	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J196	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J198	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J401	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J803	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J812	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J902	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J913	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
⚠ 3	NT801S	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	R309	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	R406	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
⚠ 3	R422S	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	R507	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	R508	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	R509	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	R717	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J162	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J105	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J112	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J153	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J183	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J204	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J209	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J177	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J211	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J212	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J199	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J184	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	C912	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	L910	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	R701	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J169	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	JK04	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J200	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	D802	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	R805	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	R850	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	R229	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J179	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J180	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J601	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J603	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J814	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	R101	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	R102	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	R708	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	J207	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	
3	R302	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
3	R306	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
3	R303	2003-002070	R-METAL OXIDE;1ohm,5%,2W,AF,TP,3.9x10mm	
3	R505	2008-000292	R-FUSIBLE(S);3.3ohm,5%,2W,AF,TP,3.9x10mm	
⚠ 3	CR409S	2201-002041	C-CERAMIC,DISC;0.82NF,10%,2KV,Y5P,TP,9X5	
⚠ 2	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
⚠ 2	P803S	1404-001156	THERMISTOR-PTC;9OHM,+30%/-20%,220VRMS,27	
⚠ 2	CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ 2	SF101S	2904-001070	FILTER-SAW AV;38.9MHz,SIP5K,TP,14.6dB,B/	
2	T401	AA26-50001B	TRANS-HORIZ.DRIVE;-,-,-,7.1mH,-,-,102uH,	
⚠ 2	LX801S	AA29-30001D	FILTER LINE NOISE;SQ1913,-,6.0MH,0.8A,-	
⚠ 2	TU01S	AA40-00076A	TUNER;TECC0949PG35A(S),PAL,181CH,38.	
2	LD901	AA96-00555A	ASSY LED GUIDE;-,-,UEX-LD-030,GREEN	
2	IC501	AA96-00842A	ASSY H/S;,VIDEO,AA62-30175D,TDA6107Q	
3	IC501	1201-001159	IC-VIDEO AMP;6107,ZSIP,9P,-,SINGLE,-,PLA	
3	SCR501	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
3	H/S501	AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	
⚠ 2	V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	
2	RM901	AA32-00015A	MODULE REMOCON;FRP-3521H31,38KHZ,940MM,M	

Level	Loc. No.	Code No.	Description ; Specification	Remark
⚠ 2	IC801S	AA96-00845A	ASSY H/S;,POWER,AA62-30186B,KA5Q0765R	
3	IC801	1203-001932	IC-PWM CONTROLLER;5Q0765,TO-220F,5P,185M	
3	SCR801	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
3	H/S801	AA62-30186B	HEAT SINK-ES;-,-,-,SILVER,171J + COVER-H	
3		HA68-02189A	LABEL-WARNING;,33MM,18MM,WHITE	
3		0205-000129	GREASE-SILICON;SC102,JAPAN	
2	IC802	AA96-00846A	ASSY H/S;,POWER,AA62-00055A,KA7632	
3	IC802	1203-001939	IC-POSI.FIXED REG.;7632,SIP,10P;-,PLASTI	
3	H/S802	AA62-00055A	HEAT SINK-PS;-,-,T1.0,-,35*15*25,D1,-,-,	
3	SCR802	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
2	T801S	AA26-00134A	TRANS SWITCHING;,CS21S5T,160V~260V,PM2 P	
2	IC902	1103-001106	IC-EEPROM;C81DC,1028x8Bit,DIP,8P,300MIL,	
⚠ 2	SW801S	3403-001134	SWITCH-PUSH;250V,5A,DPST,ON-OFF,-	
2	Q401	0502-001160	TR-POWER;2SD2499,NPN,50000mW,TO-3P,BK,8	
2	JS701	3722-000183	JACK-SCART;21P,4mm,SN,BLK,NO	
2	TOP	AA39-20010D	LEAD CONNECTOR-ASSY;,1P,400,YFH800-01,S,	
2	TOP	AA39-20010D	LEAD CONNECTOR-ASSY;,1P,400,YFH800-01,S,	
2	CN501	AA39-20620C	LEAD CONNECTOR-ASSY;,9P,500MM,YBNH250-09	
2	IC301	AA96-00847A	ASSY H/S;,AA62-00046A,LA7840	
3		1204-001483	IC-VERTICAL PROCESSO;LA7840,SIP,7P,708MI	
3		AA62-00064A	HEAT SINK-PS;DP,-,-,-,AA62-00046A,-,-,-,	
3		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
3		0205-000129	GREASE-SILICON;SC102,JAPAN	
2	C801	2401-002219	C-AL;220uF,20%,400V,GP,ST,25x40,10	
⚠ 2	T444S	AA26-00116A	TRANS FBT;FSV-14A004H(S),CT15A8,3.24MH,1	
2	SUB	AA98-00079A	ASSY SUB PART;KS1A,MAIN(OPT),PAL,-	
3		0202-000008	SOLDER-WIRE;S63S-W3.0,S63S,D3,63Sn/37Pb,	
3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	
3		0204-000442	SOLVENT;1M-1000,C3H70H,96,-	
3		0204-001024	FLUX;DF-98TVS,-,20%,-	
⚠ 2	CR410S	2306-000326	C-FILM,MPPF;4.7nF,5%,1.6KV,TP,28.5x16x9m	
2	IC602	AA96-00848A	ASSY H/S;,SOUND,AA62-30175D,TDA8943	
3	SCR602	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
3	H/S602	AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	
3	IC602	1201-001740	IC-AUDIO AMP;TDA8943,SIL,9P,850MIL,SINGL	
2	CN601	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
2	LW01	AA27-40001N	COIL HORIZ. WIDTH;-,90/260uH,SB-5S620,PI	
⚠ 2	CY801S	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
⚠ 2	CR402S	2306-000350	C-FILM,MPPF;270NF,5%,400V,TP,26X18.5X10M	
⚠ 2	LR401S	AA27-00122A	COIL LINEARITY;90UH,90UH,L81 DR10x10,7.5	
2	CN706A	AA95-01473A	ASSY ETC;,CF,KS1A,SECAM-L	
3	ICL01	1204-001583	IC-IF CIRCUIT;U4468B,DIP,16P,-,PLASTIC,5	
3	SFS01	2904-001225	FILTER-SAW AV;38.9MHz,SIP5K,ST,15.7dB,L/	
3	CN706	3711-002701	CONNECTOR-HEADER;NOWALL,3P,1R,2.5mm,ANGL	
3	CN705	3711-002708	CONNECTOR-HEADER;NOWALL,10P,1R,2.5mm,ANG	
3	CL01	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
3	CL02	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
3	CL03	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
3	CL04	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
3	CL05	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
3	CL06	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
3	CL07	2305-000196	C-FILM,MPEF;150nF,5%,63V,TP,-,5mm	
3	CL08	2305-000196	C-FILM,MPEF;150nF,5%,63V,TP,-,5mm	
3	DL01	0401-001088	DIODE-SWITCHING;BAW76,50V,300mA,DO-35,TP	
3	LL01	2701-000116	INDUCTOR-AXIAL;10uH,10%,4.2x9.8mm	
3	QL01	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
3	QL02	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
3	QL03	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
3	QL04	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
3	RL07	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	RL03	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
3	RL02	2001-000674	R-CARBON;360OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	RL05	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	RL13	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	RL11	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	RL06	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	RL10	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	RL12	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	RL15	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	RL14	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3	PCB	AA41-00468A	PCB-SECAM,L/MONO;CF2139,FR-1,1L,A,1.6T,2	
3	RL08	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
3		0203-001123	TAPE-PAPER;#53131,T0.15,W6.0,L200000,YEL	
⚠ 2	IC201S	AA09-00361A	IC MICOM;TDA9351/N2/3I,SPM-802EW4,64P,3	
2	CN401	AA60-40012D	PIN-GT,ASSY;T1.6,6-12.5-,NYLON66	
2	CN703	3711-002648	CONNECTOR-HEADER;BOX,9P,1R,2.5mm,STRAIGH	

Level	Loc. No.	Code No.	Description ; Specification	Remark
			REMOCON	
1		AA59-00104N	REMOCON;,TM59,SIM806E,29,L/GRAY,TTX/MO	
			ASSY ACCESSORY	
1		AA94-05819A	ASSY ACCESSORY;20-21,KS1A,XEF	
2		HA68-00336B	CARD-WARRANTY;A/P100(G),A5,NEW VERSION,I	
2		4301-000120	BATTERY-MN;1.5V,-,AA,14.5x50mm,-	
2		HA83-00047A	LP-TAPEACETATE;T0.1MM,W20MM,L200MM	
2		AA69-02248A	BAG ACCESSORY;,HDPE,T0.02,L350,W200	
2		HA68-02065A	MANUAL USERS;FRA,A/P100(G),31P,145,205	
2		HA68-02331A	CARD-REGISTRATION;EUROPE,2,W/P120,A5,4P	
			ASSY POWER CORD	
⚠ 1	P/CORD	AA96-01126A	ASSY POWER CORD;DP,AA39-10001G,CP2,H/C25	
2		AA39-10001G	CBF POWER CORD;-,KKP-419C,KLCE-2F,2.286m	
2		AA61-20284A	HOLDER;P-CORD,PP-,-,-,BLK,VO,KE-002	
			ASSY COVER REAR	
1		AA90-04673A	ASSY COVER REAR;21K2,KS1A	
2		AA64-02368C	CABINET BACK;21K2,KS1A	
3		AA81-00096A	RESIN-A;VL-1823,G5433,A	
2		AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	
2		AA65-30009A	CLAMPER CORE-FBT;-,ABS,V0,-,BLK,-	
			ASSY PACKING	
1		AA90-01112A	ASSY PACKING;21K2	
2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	
2		HA69-00904B	CUSHION-SET;21K2,EPS C=0.02	
3		HA83-00058A	LP-RESIN-EPS;,CHEIL SF-301V,WHT	
2		HA69-00987E	PACKING-CASE;21K2,D-2 BB,YEL,KS1B GUJU N	
2		HA68-02178A	LABEL-BOX;250MM,89MM,WHITE	
2		AA69-00744E	BAG-SHEET;-,HDPE PE FOAM,T0.015,W1300,H1	
2		HA83-00046A	LP-TAPE INK;,WIDTH 105 MM	
			ASSY COVER FRONT	
1		AA90-04715A	ASSY COVER FRONT;21K2,KS1A,SEH	
2	CB+CF	6002-000515	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(WHT),SWR	
2	PCB+CF	6003-001024	SCREW-TAPTITE;RWH,+,B,M4,L12,ZPC(YEL),SW	
2	CRT+CF	AA60-10050Q	SCREW-ASSY;-,SWRCH18A,M5,L26.5,HH,+,WC,-	
2		AA96-01637A	ASSY COVER P-FRONT;21K2,HIPS HB,KS1A,SV0	
3	KC+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
3	SPK+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
3	LED+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
3		AA61-60003T	SPRING ETC-CS;-,SUS304,-,-,OD7,N5,OD7,-,	
3		AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	
3		AA64-02092D	KNOB POWER;21K2,HIPS,HB,GD-906P,KS1A	
4		HA83-00034A	LP-MARKING PAINT;,METALLIC-CHAMPAGNE,GD-	
4		HA83-00006A	LP-RESIN HIPS;,BASF495F,NTR,HB	
4		HA83-00011A	LP-RESIN;,M BATCH,WILSON 6007-GY-60,GRY	
3		HA64-01694B	WINDOW-RMC,LED;15K2,ACRYL,CLR	
4		HA83-00010A	LP-RESIN;,OROGLAS,VM-100 ZHN 2	
3		AA64-01702C	KNOB CONTROL;21K2,HIPS,HB,GD-906P,GRY	
4		HA83-00034A	LP-MARKING PAINT;,METALLIC-CHAMPAGNE,GD-	
4		HA83-00006A	LP-RESIN HIPS;,BASF495F,NTR,HB	
4		HA83-00011A	LP-RESIN;,M BATCH,WILSON 6007-GY-60,GRY	

Level	Loc. No.	Code No.	Description ; Specification	Remark
3		AA64-02387E	CABINET FRONT;21K2,KS1A,HIPS,HB,SV012P+P	
4		HA83-00040A	LP-MARKING PAINT;,METALLIC SILVER,SV-012	
4		AA81-00106A	A/S-MARKING PAINT;,P432U,DARK GREY,TPC	
4		HA83-00039A	LP-MARKING PAINT;,PEARL WHITE,PW-001P	
4		HA83-00006A	LP-RESIN HIPS;,BASF495F,NTR,HB	
4		HA83-00016A	LP-RESIN;,M BATCH,WILSON 213-WT-60,WHITE	
3		HA64-01697B	DECORATION-POWER;DECORATION-POWER;15K2,P	
4		HA83-00009A	LP-RESIN PC;,LEXAN 121R,VIOLET	
3		HA61-00711C	HOLDER-PCB;29K8,HIPS,HB,GRY	
4		HA83-00006A	LP-RESIN HIPS;,BASF495F,NTR,HB	
4		HA83-00011A	LP-RESIN;,M BATCH,WILSON 6007-GY-60,GRY	
3		AA96-00853A	ASSY SPEAKER;,16OHM,3W,3001-001039,700	
4		3001-001039	SPEAKER;3W,16OHM,90DB,180HZ	
4		AA39-20500C	LEAD CONNECTOR-ASSY;,3(2),600,67096-003,	
3		AA64-70010B	BADGE-BRAND;-,AL,-,-,L50,-,SILVER,SS R20	
3		HA83-00049A	LP-ADHESIVE-HM;12MM,NTR	
3		0203-001290	TAPE-OPP MASKING;ANT 100C,T0.073,W30,L50	
3		AA61-40113A	STOPPER-PCB;501H,HIPS,-,-,HB,NTR,-	
2		HA68-02179A	LABEL-RATING;58MM,53MM,WHITE	
2	qms	HA83-00052A	LP-TAPE-INK;,WIDTH 55 MM	
2	rating	HA83-00052A	LP-TAPE-INK;,WIDTH 55 MM	
2		AA64-00894K	INLAY-BACK;21K2,PS SHEET,T0.3,BLK,KS1B 1	
2		AA65-30111A	CLAMPER CORE-WIRE;ALL MODEL,NYLON,V0,-,W	
2		HA68-02177B	LABEL-PQS;ALL,30MM,65MM,WHITE,AA68-02177	

ASSY CPT

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA91-06621A	ASSY CPT;,21,+380MG,A51ERF135X85,KS1A	
⚠ 2		AA03-00366A	CRT COLOR;A51ERF135X85,+380MG,2.3MH,27MH	
2		AA27-00130A	COIL DEGAUSSING;-,-,-,-,40T,9ohm,-,21inc	
2		AA65-30107A	CLAMPER CORE-D,COIL;20~22 INCH,NYLON 66,	
2		AA98-70030A	ASSY TBC WIRE(P);DP,21,AA98-70014C,1P,TV	

You can search for the updated part code through ITSELF web site.
URL : http://itself.sec.samsung.co.kr

7-2 CS21D8SX/RNK

ASSY CHASSIS

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA91-06316A	ASSY CHASSIS;CS21D8SX/RNK,KS1A	
2		0201-001096	ADHESIVE-HM;#3748,YEL,8500CPS,-	
2		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	
2		0202-001044	SOLDER-WIRE.;S63S-W3.0,S63S,D3,63SN/37PB	
2		0202-001046	SOLDER-WIRE FLUX;CF-110VH-2A,-,-,-,-	
2		0203-000147	TAPE-PAPER;3M_#209,T0.14,W30,-,NTR	
2		0203-000457	TAPE-VINYL;#270,T0.175,W19.0,L10.0 MT,BL	
2		0204-001095	THINNER;#4520,-,-,-	
2		0205-000129	GREASE-SILICON;SC102,JAPAN	
2		AA65-30002A	CLAMPER CORE-FBT;-,NYLON-66,V0,-,BLK,-	
2		AA94-12942A	ASSY PCB MAIN;CS21D8SX/RNK,KS1A	
3		0204-000166	SILICON;DCI-2577,SIO2,75%,-	
3	Q401	0502-001160	TR-POWER;2SD2499,NPN,50000mW,TO-3P,BK,8-	
⚠ 3	PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
3	IC902	1103-001106	IC-EEPROM;C81DC,1028x8Bit,DIP,8P,300MIL,	
3	IC101	1204-001583	IC-IF CIRCUIT;U4468B,DIP,16P,-,PLASTIC,5	
⚠ 3	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
⚠ 3	P803S	1404-001156	THERMISTOR-PTC;9OHM,+30%/-20%,220VRMS,27	
⚠ 3	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
3	R801	2003-002171	R-METAL OXIDE(S);150ohm,5%,2W,AG,TP,3.9x	
3	R402	2003-002178	R-METAL OXIDE(S);1Kohm,5%,2W,AG,TP,3.9x1	
3	R407	2003-002209	R-METAL OXIDE(S);47Kohm,5%,2W,AG,TP,3.9X	
3	R814	2003-002228	R-METAL OXIDE(S);0.47ohm,5%,2W,AG,TP,3.9	
3	R815	2003-002228	R-METAL OXIDE(S);0.47ohm,5%,2W,AG,TP,3.9	
3	R420	2008-001110	R-FUSIBLE(S);68ohm,5%,2W,AG,TP,3.9X12mm	
⚠ 3	CY801S	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
⚠ 3	CR409S	2201-002028	C-CERAMIC,DISC;0.47NF,10%,2KV,Y5P,TP,7.5	
⚠ 3	CR402S	2306-000188	C-FILM,MPPF;330nF,5%,400V,TP,26x19.5x11,	
⚠ 3	CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ 3	CR410S	2306-000327	C-FILM,MPPF;6.3nF,3%,1.6KV,TP,28.5x18x10	
3	C801	2401-002213	C-AL;150uF,+30-10%,450V,GP,BK,25x35	
⚠ 3	SF101S	2904-001143	FILTER-SAW AV;38.9MHz,SIP5K,ST,18dB,B/G,	
⚠ 3	SF102S	2904-001224	FILTER-SAW AV;38.9MHz,SIP5K,ST,16.3dB,B/	
⚠ 3	SW801S	3403-001107	SWITCH-PUSH;250V,5A,DPST,-,KDC-A04	
⚠ 3	FP801S	3601-000281	FUSE-CARTRIDGE;250V,4A,TIME-LAG,GLASS,5.	
⚠ 3	V999S	3704-001090	SOCKET-CRT;9P,15.24PI,26.5PI,SN,-	
3	CN602	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
3	JS701	3722-000497	JACK-PIN;4P,3.4mm,SN,BLK,-	
3		AA09-00356A	IC MICOM;TDA9381/N2/3I,SPM-802EAN4,64P,3	
3	HIC01	AA13-20004W	IC HYBRID;-,PAP103T,SIP,6P,PRE-AMP,TP	
3	T101	AA26-00025A	TRANS RF;7MG,-,-,-,10pF,-,58.35MHz,7.7x7	
⚠ 3	T801S	AA26-00043A	TRANS SWITCHING;-,-,-,-,AC90~260V,125/12.5	
⚠ 3	T444S	AA26-00065A	TRANS FBT;-,FSV-14A004C(S),14-22,125V	
3	T401	AA26-50001B	TRANS-HORIZ.DRIVE;-,-,-,7.1mH,-,-,102uH,	
⚠ 3	LR401S	AA27-00053A	COIL LINEARITY;-,193uH,DR10X10 C:4.35,7.	
3	LW01	AA27-40001N	COIL HORIZ. WIDTH;-,90/260uH,SB-5S620,PI	
⚠ 3	LX801S	AA29-30001B	FILTER LINE NOISE;-,-,-,-,27MH,-,-,-,ST,	
3		AA39-20010D	LEAD CONNECTOR-ASSY;,1P,400,YFH800-01,S,	
3	CN501	AA39-20620C	LEAD CONNECTOR-ASSY;,9P,500MM,YBNH250-09	
⚠ 3	TU01S	AA40-00076A	TUNER;TECC0949PG35A(S),PAL,181CH,38.9MHZ	
3	RM901	AA32-00015A	MODULE REMOCON;FRP-3521H31,38KHZ,940MM,M	
3	GT401	AA60-40012D	PIN-GT,ASSY;T1.6,6-12.5-,NYLON66	
3		AA65-30009A	CLAMPER CORE-FBT;-,ABS,V0,-,BLK,-	
3	CLAMP	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-	
3		AA65-30111A	CLAMPER CORE-WIRE;ALL MODEL,NYLON,V0,-,W	
3		AA68-00772A	LABEL WARNING;ALL (D),ART PAPER,28,40,WH	
3		AA68-00773A	LABEL CAUTION;ALL (D),ART PAPER,16,35,WH	
⚠ 3	IC801S	AA96-00242A	ASSY H/S;-,-,AA62-30186B,KA5Q0765R,-	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	
4		1203-001932	IC-PWM CONTROLLER;5Q0765,TO-220F,5P,185M	
4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	
4		AA62-00063A	HEAT SINK-ES;DP,-,-,-,AA62-30186B,-,-,-	
5	-	0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
5	-	AA62-30186B	HEAT SINK-ES;-,-,-,SILVER,171J + COVER-H	
5	223	AA69-01402A	PAD-PLATE;,CB DW-2,YEL,100,100	
5	-	AA69-40004F	MASTER CARTON;-,CB SW-2,-,355,265,255,YE	
⚠ 3	D806	AA96-00243D	ASSY H/S;-,BRIDGE,AA62-00045A,D06U20S,DR	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	
4		0402-001374	DIODE-RECTIFIER;FFPF06U20S,200V,6A,TO-22	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	
4		AA62-00065A	HEAT SINK-PS;DP,-,-,-,AA62-00045A,-,-,-	
5	-	0203-000435	TAPE-OPP MASKING;OPP,T0.07,W50,L500,YEL	
5	-	0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
5	-	AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-	
5	-	AA69-10165J	PAD-PLATE;CB SW-2,YEL,340,250,-,-,663,-	
5	-	AA69-40004A	MASTER CARTON;-,CB DW-3,-,355,265,175,YE	
3	IC301	AA96-00244A	ASSY H/S;-,-,AA62-00046A,LA7840,-	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	
4		1204-001483	IC-VERTICAL PROCESSO;LA7840,SIP,7P,708MI	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	
4		AA62-00046A	HEAT SINK-PS;-,-,T1.0,-,D1(DREAM) 60X25X	
3	IC601	AA96-00244G	ASSY H/S;-,AUDIO,AA62-00046A,TDA8944J,BR	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	
4		1201-001741	IC-AUDIO AMP;TDA8944J,DBS,17P,937MIL,DUA	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	
4		AA61-10162B	BRACKET-IC;-,SBHG-1,T1.0,-,-,-,100	
4		AA62-00046A	HEAT SINK-PS;-,-,T1.0,-,D1(DREAM) 60X25X	
3	IC802	AA96-00245A	ASSY H/S;-,-,AA62-00055A,KA7632,-	
4		1203-001939	IC-POSI.FIXED REG.;7632,SIP,10P,-,PLASTI	
4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
4		AA62-00074A	HEAT SINK-PS;DP,AA62-00055A,-,-,-,-,-,-,	
5	-	0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
5	-	AA62-00055A	HEAT SINK-PS;-,-,T1.0,-,35*15*25,D1,-,-,	
5	-	AA69-10042F	PAD-PLATE;CB DW-2,YEL,350,260,-,-,-,-	
5	-	AA69-10116J	PAD-PLATE;CB DW-2,YEL,345,40,-,-,-,-	
5	-	AA69-40004A	MASTER CARTON;-,CB DW-3,-,355,265,175,YE	
3	LD901	AA96-00555A	ASSY LED GUIDE;-,-,UEX-LD-030,GREEN	
3	IC501	AA96-50311A	ASSY H/S;-,VIDEO,AA62-30175D,TDA6107Q,-	
4		1201-001159	IC-VIDEO AMP;6107,ZSIP,9P,-,SINGLE,-,PLA	
4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
4		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	
3		AA97-13981A	ASSY AUTO-MAIN;CS21D8SX/RNK,KS1A	
4	D101	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D103	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D305	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D804	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D808	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D811	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D901	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D501	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
4	D803	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
⚠ 4	D805	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
4	D301	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
4	D304	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
⚠ 4	D401	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
4	D502	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
4	D503	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
4	D504	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
⚠ 4	D812	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
⚠ 4	D801S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D802	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D802S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D803S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4	D804S	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
4	D303	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
4	D809	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
4	D302	0402-001352	DIODE-RECTIFIER;GUF15G-20A,400V,1.5A,DO-	
4	DZ402	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ807	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ810	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ904	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZ905	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	DZ803	0403-000699	DIODE-ZENER;TZP27B,27V,27-30.8V,1W,DO-41	
4	DZ101	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
4	DZ303	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
4	DZ804	0403-000719	DIODE-ZENER;MTZJ7.5B,7.5V,7.07-7.45V,500	
4	DZ201	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ204	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ205	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ207	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ306	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ307	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ501	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ502	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ503	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ504	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ704	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ808	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4	DZ801	0403-001140	DIODE-ZENER;RD10ESAB-T4,10V,9.19-10.30V,	
4	DZ302	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
4	DZ806	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
4	DZ802	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500mW,DO	
4	DZ901	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ906	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ907	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ908	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ401	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
4	DZ203	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
4	DZ805	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
4	DZ301	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
4	DZ305	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
4	Q201	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q203	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q206	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q301	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q901	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q402	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
4	Q101	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q102	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q202	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q204	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q205	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q701	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q702	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q802	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q903	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q905	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	Q703	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,T	
4	Q902	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,T	
4	IC803	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
4	R710	2001-000004	R-CARBON;200KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R207	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
4	R905	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
4	R906	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
4	R103	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R111	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R218	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R205	2001-000011	R-CARBON;75KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	J125	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
4	R301	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
4	R618	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R619	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R843	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R409	2001-000022	R-CARBON(S);33OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R823	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R808	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R230	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R902	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R904	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R313	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R923	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	J137	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R101	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R102	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R211	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R215	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R223	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R225	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	R501	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R502	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R506	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R510	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R511	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R512	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R708	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R909	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R911	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R912	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R913	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R914	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R933	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R934	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R938	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R106	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R118	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R224	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R307	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R828	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R910	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R919	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R920	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R921	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R922	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R924	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R928	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R937	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R214	2001-000325	R-CARBON;120OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R932	2001-000325	R-CARBON;120OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R212	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R104	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R113	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R717	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R918	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R926	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R931	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R916	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R917	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R220	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R901	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R903	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R907	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R908	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R206	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R829	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R929	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R105	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R112	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R208	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R202	2001-000689	R-CARBON;390KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R721	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R830	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R841	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R925	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R227	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R228	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R109	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R704	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R209	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R927	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R203	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R204	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R210	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R713	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R715	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R601	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R607	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R110	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R117	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R915	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R213	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R108	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R222	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R701	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R702	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	R719	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R720	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R408	2001-001037	R-CARBON(S);0.39OHM,5%,1/2W,AA,TP,2.4X6.	
4	R504	2001-001062	R-CARBON(S);10MOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R414	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R840	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R832	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R308	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R411	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R405	2001-001116	R-CARBON(S);27OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R821	2001-001125	R-CARBON(S);300KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R809	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R810	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R805	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R850	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R831	2001-001192	R-CARBON(S);820OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
4	R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
4	R503	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
⚠ 4	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
4	R314	2003-000537	R-METAL OXIDE(S);1Kohm,5%,1W,AF,TP,3.3x9	
4	R403	2003-000784	R-METAL OXIDE(S);7.5Kohm,5%,2W,AF,TP,4x1	
4	R803	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,AF,TP,3.9x	
4	R804	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,AF,TP,3.9x	
4	R827	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
4	R834	2003-001040	R-METAL OXIDE(S);47Kohm,5%,2W,AF,TP,3.9x	
4	R315	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x	
4	R316	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x	
4	R303	2003-002070	R-METAL OXIDE;1ohm,5%,2W,AF,TP,3.9x10mm	
4	R413	2003-002130	R-METAL OXIDE(S);15ohm,5%,2W,AF,TP,3.9x1	
4	R602	2004-000699	R-METAL;3.3Kohm,1%,1/8W,AA,TP,1.8x3.2m	
4	R605	2004-000699	R-METAL;3.3Kohm,1%,1/8W,AA,TP,1.8x3.2m	
4	R820	2004-001371	R-METAL(S);1.5Kohm,1%,1/2W,AA,TP,2.4x6.4	
4	R423	2004-001373	R-METAL(S);100Kohm,1%,1/2W,AA,TP,2.4x6.4	
4	R819	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
4	R818	2004-001399	R-METAL(S);5.1Kohm,1%,1/2W,AA,TP,2.4x6.4	
4	R424	2004-001402	R-METAL(S);6.8Kohm,1%,1/2W,AA,TP,2.4x6.4	
4	R219	2004-001914	R-METAL;39Kohm,2%,1/8W,AA,TP,1.8x3.5mm	
4	R822	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
4	R817	2004-004089	R-METAL(S);123Kohm,1%,1/2W,AA,TP,2.5x6.5	
4	R302	2004-004366	R-METAL(S);1.3Kohm,1%,1/2W,AA,TP,2.5x6.5	
4	R306	2004-004366	R-METAL(S);1.3Kohm,1%,1/2W,AA,TP,2.5x6.5	
4	R304	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
4	R305	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
4	R825	2008-000266	R-FUSIBLE(S);1ohm,5%,2W,AF,TP,3.9x10mm	
4	R824	2008-000294	R-FUSIBLE(S);33ohm,5%,2W,AF,TP,3.9x10mm	
4	R505	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
4	R421	2008-001133	R-FUSIBLE(S);0.75ohm,5%,2W,AF,TP,3.9x10m	
4	C302	2201-000259	C-CERAMIC,DISC;0.18NF,10%,500V,Y5P,TP,5.	
4	C816	2201-000375	C-CERAMIC,DISC;0.22NF,5%,50V,RH,TP,12.5X	
4	C303	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
4	C305	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
4	C908	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
4	C909	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
4	C408	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
4	C114	2201-000611	C-CERAMIC,DISC;0.056NF,5%,50V,C0G,TP,7X3	
⚠ 4	CR404S	2201-000639	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
4	C503	2201-000723	C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,16X5	
4	C811	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
4	C814	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
4	C703	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
4	C704	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
4	C912	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
4	C105	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
4	C106	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
4	C108	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
4	C111	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
4	C117	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
4	C702	2202-000210	C-CERAMIC,MLC-AXIAL;270pF,10%,50V,Y5P,TP	
4	C102	2202-000279	C-CERAMIC,MLC-AXIAL;47pF,5%,50V,SL,TP,3.	
4	C115	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
4	C211	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
4	C826	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
4	C911	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
4	C107	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C223	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C224	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C906	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C104	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C505	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
4	C226	2202-000829	C-CERAMIC,MLC-AXIAL;0.82NF,10%,50V,Y5P,T	
4	C810	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
4	C707	2301-000204	C-FILM,PEF;2.7nF,5%,50V,TP,7.4x3.9x13mm,	
4	C502	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
4	C109	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
4	C804	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
4	C805	2301-000235	C-FILM,PEF;3.9nF,5%,50V,TP,6.5x3.0x5.5mm	
4	C309	2301-000254	C-FILM,PEF;39nF,5%,50V,TP,7.5x3.5x6.5mm,	
4	C606	2301-000289	C-FILM,PEF;5.6nF,5%,50V,TP,7x6x3,5	
4	C610	2301-000289	C-FILM,PEF;5.6nF,5%,50V,TP,7x6x3,5	
4	C217	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
4	C234	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
4	C118	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
4	C407	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
4	C904	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
4	C227	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
4	C248	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
4	C420	2301-001065	C-FILM,MPPF;47nF,5%,630V,TP,19x15.5x7,7.	
4	C806	2301-001435	C-FILM,PPF;1.5nF,5%,1.2kV,TP,15x8x12.5mm	
4	C312	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
4	C301	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
4	C215	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C216	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C233	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C603	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C607	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C611	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C613	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
⚠ 4	CR405S	2305-000382	C-FILM,MPEF;4.7nF,5%,400V,TP,-,5mm	
4	C121	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
4	C207	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
4	C901	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
4	C103	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C208	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C210	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C218	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C230	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C618	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C619	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C803	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C819	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C913	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C225	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
4	C119	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
4	C120	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
4	C310	2401-000215	C-AL;0.1UF,20%,50V,GP,TP,4X7MM,5	
4	C812	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
4	C817	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
4	C821	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
4	C823	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
4	C915	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
4	C307	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
4	C308	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
4	C506	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
4	C708	2401-000471	C-AL;10uF,20%,50V,BP,TP,5x11,5mm	
4	C612	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
4	C820	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
4	C403	2401-000560	C-AL;1uF,20%,160V,GP,TP,6.3x11,5	
4	C219	2401-000603	C-AL;1UF,20%,50V,GP,TP,5X11,2	
4	C212	2401-000649	C-AL;2.2uF,20%,50V,BP,TP,5x11,5	
4	C221	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
4	C604	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
4	C605	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
4	C822	2401-000711	C-AL;2200uF,20%,25V,GP,TP,16x25,7.5	
4	C222	2401-000758	C-AL;0.22UF,20%,50V,GP,TP,5X11,5	
4	C110	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
4	C113	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
4	C709	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
4	C827	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
4	C101	2401-001101	C-AL;330uF,20%,16V,GP,TP,8x11.5,5	
4	C203	2401-001176	C-AL;33uF,20%,25V,GP,TP,5x11,5	
4	C802	2401-001192	C-AL;33uF,20%,50V,GP,TP,6.3x11,5	
4	C504	2401-001232	C-AL;4.7uF,20%,250V,GP,TP,10x12.5,5	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	C209	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C213	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C214	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C229	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C903	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C910	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C706	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
4	C601	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
4	C206	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	C220	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	C304	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
4	C306	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
4	C813	2401-002290	C-AL;47uF,20%,160V,GP,TP,13x20,5	
4	C406	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
4	C818	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
4	L103	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L202	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L203	2701-000127	INDUCTOR-AXIAL;15uH,10%,2.5x3.4mm	
4	L301	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
4	L302	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
4	L404	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
4	L903	2701-000158	INDUCTOR-AXIAL;22uH,10%,2.5x3.4mm	
4	L201	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
4	L205	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
4	L405	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
4	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
4	L104	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
4	L902	2701-000180	INDUCTOR-AXIAL;33uH,5%,2.5x3.4mm	
4	L904	2701-000180	INDUCTOR-AXIAL;33uH,5%,2.5x3.4mm	
4	L204	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
4	L703	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
4	L706	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
4	L101	2701-000326	INDUCTOR-AXIAL;0.56UH,10%,2.3X3.4MM	
4	L804	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
4	L807	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
4	X901	2801-003433	CRYSTAL-UNIT;12MHZ,30PPM,28-AAM,30PF,30O	
4	L403	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	L806	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	L808	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	Z201	2903-000129	FILTER-CERAMIC;BR,4.5MHz,-,-,-,TP,-	
4	Z202	2903-001240	FILTER-CERAMIC;TR,5.5MHz,-,28dB,-,TP,-	
4	Z203	2903-001040	FILTER-CERAMIC;TR,5.5/6.0/6.5MHz,-,1dB,-	
4	J910	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	L802	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	L803	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	SW901	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
4	SW902	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
4	SW903	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
4	SW904	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
4	SW905	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
⚠ 4	FD801S	3601-001163	FUSE-AXIAL LEAD;125V,7A,-,EPOXY,2.4X7.1M	
4	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
4	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
4	C507	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	C508	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	D202	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J101	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J102	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J103	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J104	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J105	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J106	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J107	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J110	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J112	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J113	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J114	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J115	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J116	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J117	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J118	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J120	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J121	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J122	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J123	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J124	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J126	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J127	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J128	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J129	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J131	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J132	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J133	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J134	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J135	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J136	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J138	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J139	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J140	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J141	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J142	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J143	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J145	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J146	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J147	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J148	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J149	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J150	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J151	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J152	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J153	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J154	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J155	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J156	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J157	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J158	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J159	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J160	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J163	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J167	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J168	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J169	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J170	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J171	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J173	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J174	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J175	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J176	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J177	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J179	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J180	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J181	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J182	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J183	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J184	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J185	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J186	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J187	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J189	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J190	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J192	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J193	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J195	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J196	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J198	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J199	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J200	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J204	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J207	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J209	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J211	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J212	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J401	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J601	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J603	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J705	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J711	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J803	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J807	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J812	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J814	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J902	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	JK01	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	JK02	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	JK03	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	JK04	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	L910	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
⚠ 4	NT801S	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R107	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R229	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R309	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R406	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
⚠ 4	R422S	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R507	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R508	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R509	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R703	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	R705	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J213	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	J214	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
4	PCB	AA41-00131H	PCB-MAIN;CS21D8,FR-1,1L,H,1.6T,245X245,K	
4	EY101	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY401	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY402	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY403	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY404	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY405	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY406	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY407	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY408	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY409	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY410	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY411	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY412	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY414	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY415	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY416	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY417	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY419	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY420	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY421	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY422	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY423	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY501	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY801	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY802	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY803	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY807	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY808	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY809	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY810	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY813	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY818	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY819	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY821	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY822	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY823	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY824	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY825	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY827	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY828	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY829	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY830	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY833	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY850	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY851	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY852	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY853	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY860	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EY861	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	
4	EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
4	EL404	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
4	EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
4	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
4	EL804	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	
4	GT101	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT801	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	
4	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	
⚠ 2		AA96-00043A	ASSY POWER CORD;-,RVVB 2X075.240,EP2/YES	
3		AA39-00096B	CBF POWER CORD;-,RVVZ-2P,RVVB 2X0.75,240	
3		AA61-00632A	HOLDER;2163(TTSEC),NYLON ,BLK ,V0	

ASSY ACCESSORY

1		AA92-07834A	ASSY ACCESSORY;CS21D8SX/RNK,KS1A	
2		4301-000120	BATTERY-MN;1.5V,-,AA,14.5x50mm,-	
2		AA59-00104J	REMOCON;,TM59,SIM806E,24,L/GRAY,EX,GRAY	
2		AA68-01602B	MANUAL USERS;,ENG,W/P100G,ALL1,B5,KS1A,3	
2		AA68-02638A	LABEL SERIAL;ALL (TTSEC),90G,11,32,WHITE	
2		AA69-30002A	BAG-SHEET;LDPE,T0.05,W240,L400,-,L-TYPE,	

ASSY BOX

1		AA92-07835A	ASSY BOX;CS21D8SX/RNK,KS1A	
2		AA68-50509A	LABEL-BOX;A/P 90(G),ALL MODEL,-,WHT,L250	
2		AA69-01455B	PACKING CASE;CS21D8SX/RNK,PAPER,DW-2,7.5	

ASSY P/MATERIAL

1		AA92-07836A	ASSY P/MATERIAL;CS21D8SX/RNK,KS1A	
2		0203-001269	TAPE-OPP MASKING;#301,T0.06,W75,L50000,N	
2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	
2		AA69-00674B	CUSHION-SET;21D8,EPS,-,-,-,-,-,C=0.02,-	
2		AA69-30032D	BAG-SHEET;HDPE+PE FOAM,-,W1200,H1200,-,-	

ASSY COVER FRONT

1		AA90-04635A	ASSY COVER FRONT;CS21D8SX/RNK,KS1A	
2	SPK+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
2	CB+JCK	6003-001025	SCREW-TAPTITE;RH,+,B,M4,L20,ZPC(BLK),SWR	
2		6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	
2	CRT+CF	AA60-10050R	SCREW-ASSY;-,SWRCH18A,M5,L31.5,HH,+,WC,-	
2		AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-	
2		AA65-30107A	CLAMPER CORE-D,COIL;20~22 INCH,NYLON 66,	
2		AA96-01542A	ASSY COVER P-FRONT;CS21D8SX/RNK,KS1A	
3		0103-001229	RESIN-HIPS;HR-1360,GRY,C7425,HB	
3		0201-000281	ADHESIVE-RBR;D-5250,YEL,6000CPS+-500	
3		0203-001272	TAPE-OPP MASKING;#2327,T0.15,W24,L50M,YE	
3		0203-001290	TAPE-OPP MASKING;ANT 100C,T0.073,W30,L50	
3		0204-001422	THINNER;T-402,C5H10O2,95%,16KG	
3		0206-001280	MARKING-PAINT;PG-60(SV-012P),SIL/WHT,GB1	
3		0206-001281	MARKING-PAINT;PG-60(DB-004P),GREEN,GB172	
3	KC+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	
3	WIN+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	
3		AA61-40113A	STOPPER-PCB;501H,HIPS,-,-,HB,NTR,-	
3	POWER	AA61-60003J	SPRING ETC-CS;-,SUS304,-,-,OD6,N7,OD6,-,	
3		AA63-60001X	SPACER-FELT;-,FELT,-,-,-,BLK,T0.5,-,330X	
3		AA64-01011B	INDICATOR LED;29D8,ACRYL,-,CLR,-,-,-	
3		AA64-01012E	KNOB CONTROL;29D8(TTSEC),ABS,HB,G3676,SV	
3		AA64-03625A	CABINET;CS21D8SX/RNK,HIPS,T2.5,HB,SV012P	
3		AA64-01425C	KNOB POWER;21D8(TTSEC),ABS,HB,G3676,SV-0	
3		AA64-01426B	WINDOW REMOCON;21D8,PC,-,-,-,VOILET,-,-	
3		AA64-70123B	BADGE-BRAND;-,AL,-,-,L=50,SAMSUNG,SILVER	
3		AA65-30105B	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	
2		AA96-10146C	ASSY SPEAKER;-,8ohm,5W,3001-000274,350/7	
3		3001-000274	SPEAKER;5W,8OHM,90DB,160HZ	
3		AA39-20505M	LEAD CONNECTOR-ASSY;,4P,350,700MM,YSH025	

Level	Loc. No.	Code No.	Description ; Specification	Remark

Level	Loc. No.	Code No.	Description ; Specification	Remark

ASSY COVER REAR

1		AA90-04636A	ASSY COVER REAR;CS21D8SX/RNK,KS1A	
2		AA60-00091J	SPACER-FELT;-,FELT,330X10,-,-,BLK,T0.5,-	
2	BACK	AA60-00096L	SPACER-FELT;CS21D9X(TTSEC),FELT,L250,BLK	
2		AA64-01422B	CABINET BACK;21D8,HIPS,-,-,-,HB,BLK,-	
3		0103-001229	RESIN-HIPS;HR-1360,GRY,C7425,HB	
2		AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	

ASSY CPT

1		AA91-02935A	ASSY CPT;CS21D8SX/XTT	
2		AA27-00144A	COIL DEGAUSSING;,48T,9OHM,21INCH,110/220	
2		AA97-01360A	ASSY CRT;A51KQJ63X02(H),+380MG,21	
3		0203-000432	TAPE-ACETATE;#156A,T0.25MM,W19MM,L30M,WH	
⚠ 3		AA03-10024T	CRT COLOR;A51KQJ63X(H),+380mG,2.28mH,22.	
3		AA27-00002A	MAGNET CONVERGENCE;-,JH291-SC-OB,29.1MM	
3		AA27-50004K	DEFLECTION YOKE;-,DST-2192ML(H1),ST-3,A5	
3		AA63-60028A	SPACER-DY;-,NEOPRENE,-,-,-,BLK,-,-,V0 W1	
3		AA71-00003A	STICK FERRITE;,T0.35,W5.0,L90.0,D/K,15.0	
3		AA71-00004A	STICK FERRITE;,T0.35,W10.07,L100,D/K,25	
2		AA98-00046D	ASSY TBC WIRE(P);-,21,PAL,1P,-	